



# 6 Zone Mixer with Voice Recorder T-6245



## Features

- \* Mixer with 6 zone speaker selector for source selection and zone control.
- \* Built-in mic and recorder for easy voice message recording and storage.
- \* 3 audio sources direct selection on front panels.
- \* 6 zone selection buttons on front panel.
- \* 6 zone paging console work together with the mixer through RJ45 port for remote control and announcement.
- \* Mic input by XLR type with phantom power and gain control.
- \* 3 aux inputs for tape, CD and tuner.
- \* Built-in chime, whose remote trigger and volume is provided.
- \* 3 voice messages broadcast in continuous and once modes.
- \* 3 channel pre outputs: music, music/page and page.
- \* 6 zone line outputs for power amplifier.
- \* Volume control is provided for mic, music, mater, record and message broadcast, plus bass and treble tone control.
- \* Indications include zone selector, source selector, record state, power and output level meters.
- \* 4 levels of priority from high to low: remote paging console, Mic1, chime, pre-recorded message broadcast.

## Specifications

|                                            |                                                    |
|--------------------------------------------|----------------------------------------------------|
| Model                                      | T-6245                                             |
| CONSOLE INPUT                              |                                                    |
| Sensitivity                                | 5 mV/600Ω, 500mV/10KΩ                              |
| S/N Ratio                                  | >68dB                                              |
| Frequency Response                         | 50Hz~17KHz (+1, -3dB)                              |
| MIRCOPHONE INPUT                           |                                                    |
| Sensitivity                                | 5 mV/600Ω, 500mV/10KΩ                              |
| S/N Ratio                                  | >68dB                                              |
| Frequency Response                         | 50Hz~17KHz (-3dB)                                  |
| Phantom Power                              | +48V                                               |
| 3 AUXILIARY INPUTS                         |                                                    |
| Tuner and Tape Input Sensitivity/Impedance | 200mV/47Ω                                          |
| CD Input Sensitivity/Impedance             | 500mV/47Ω                                          |
| S/N Ratio                                  | >90dB                                              |
| Frequency Response                         | 20Hz~20KHz (+1, -3dB)                              |
| CONTROL                                    |                                                    |
| Bass                                       | ±12dB at 100Hz                                     |
| Treble                                     | ±12dB at 10KHz                                     |
| Chime                                      | 2 tone active for contact free in priority and BGM |
| Normal Distortion                          | >0.05%                                             |
| OPERATING CONDITION                        |                                                    |
| Power Supply                               | ~110V-230V 50/60Hz & DC 24V                        |
| Dimensions                                 | 484 x 303 x 88mm                                   |
| Weight                                     | 6.32Kg                                             |
| Max number of paging console               | 6                                                  |

## Rear Panel

